



Sample image

DH10-1

Type Size: S0

Classification Contact: Rigid contact bridge

Classification Contact Mat: Gold

Classification Terminal: Screw terminal

IEC 60947-3 EN 60947-3, VDE 0660 Teil 107

Rated insulation voltage U_i

Voltage (V)	AC / DC
690	AC

Rated impulse withstand voltage U_{imp}

Voltage (kV)	Oversvoltage category	Pollution degree	Supply system	Function
6	III	3	Valid for lines with grounded common neutral termination	Switch

Rated uninterrupted current I_u /Ith

Current (A)	Ambient temperature (°C)	Peak temperature (°C)	additional requirements
16	55	60	Ambient temperature +55°C during 24 hours with peaks up to +60°C

Rated operational current I_e

Utilization category	Voltage (V)	Current (A)
AC-15	220 - 240	1,50
AC-15	380 - 440	1
AC-21A	12 - 690	16

Max. Fuse rating IEC

Fuse characteristic	No. of Fuses	Current (A)
gG	1	16

UL60947-4-1, UL508

Rated insulation voltage U_i

Voltage (V)	AC / DC
600	AC

Rated thermal current

Current (A)	Ambient temperature (°C)	Additional Text
12	0 - 40	-

GENERAL TECHNICAL INFORMATION

Tightening torque of screws

tightening torque (Nm)	tightening torque (lb-in)
0,60	5

Rated short-time withstand current I_{cw}

Time (s)	Current (A)
1	150

Size of conductor

composition of conductor	Min. / Max. value	No. of conductor per terminal	Cross section (mm ²) or (AWG/kcmil)	Material of the wire
Flexible wire	Max.	2	2.5mm ²	Copper
Flexible wire	Max.	2	AWG 14	Copper
Single-core or stranded wire	Max.	2	AWG 12	Copper
Single-core or stranded wire	Max.	2	2.5mm ²	Copper
Flexible wire with ferrule according to DIN 46228	Max.	2	1.5mm ²	Copper

Approbations

Specification	Marking
---------------	---------

EAC



CE marking



Approbations		
<i>Specification</i>		<i>Marking</i>
UK Directives		
IEC 60947-3; EN 60947-3; VDE 0660 Teil107		IEC 60947-3 EN 60947-3
UL 60947-4-1; CSA C22.2 No. 60947-4-1		cRAUS
Power loss per pole		
		<i>Power (W)</i>
		1,30
Conditions during transport and storing		
<i>Minimum temperature (°C)</i>	<i>Maximum temperature (°C)</i>	<i>additional requirements</i>
-40	85	In case of temperatures below -5°C no shock load permissible
General Information		
<i>Text</i>		
<ul style="list-style-type: none"> - Use only copper wires with or without tinned/silver-plated individual wires. Soldering the end of the wire before wiring is not allowed. - Terminals with factory fitted jumper links are tightened during production for loss prevention. When opening the terminal clamps, make sure that no factory fitted links get lost and that all wire connections are properly seated. - After wiring, ALL terminal screws must be tightened to the specified torque values. - The protection class of the selected mounting type may vary if optional extras are used. - Do not lubricate or treat contacts. - Switches may only be mounted, connected and set into operation by qualified persons according to the accepted rules of technology. - After installation of the switches the spacings between the terminals must be sufficient to fulfill the requirement of the applicable standards. 		
Operating temperature		
	<i>Min. Temperature [°C]</i>	<i>Max. Temperature [°C]</i>
	-25	60